


AUTOMATIC CONSTANT
SIX FUNCTIONS
FLOATING DECIMAL

con/us

CONTENTS

Identification of Switches	3	Subtraction	6
	3	Multiplication	6
	0	Division	7
Calculates Operation		Mixed Calculations	7
Calculator Operation	4	Square Root	8
Numeric Keys and Decimal Point	2 J 040	C Reciprocal	8
Clearing Keys	_ 4	Percentage	9
Operation Keys Datamath	Calc	lat Constant Seum	10
	-	Powers	13
Numeric and Symbol Display	5	Clearing	13
Floating Decimal	5	Overflow	14
Reciprocals	5		
Powers	5		
		Maintenance	15
Calculator Examples	6		
Addition	6	Glossary	15



8-DIGIT MULTI-FUNCTION CALCULATOR

Today's most advanced MOS "calculator-on-achip" integrated circuitry provides instant addition, subtraction, multiplication, square root, percentages and division.

- Automatic constant operations with all functions
- Six functions (+, -, ×, +, %, √x)
- Floating decimal
- Enter problems the way you write them
- True credit balance
- Mixed calculations
- LED display: 8 digits and sign
- Unique positive-touch keyboard
- Small and lightweight
- Battery-operated
- Low power consumption for longer battery life
- Optional AC adaptor

CALCULATOR OPERATION

ON-OFF SWITCH

The On-Off switch is located on the top end of the calculator case (see Figure 1).

NUMERIC KEYS

0 - 9 These keys are used to enter the numbers.

DECIMAL KEY

In decimal fractions, this key is used to enter the decimal point in its proper place.

CLEARING KEYS

- This key clears all information stored in the calculator including any displaced number, in preparation for a new problem. Returns display to a single zero and decimal point (0.).
- You can use this key to "erase" or clear a number entered by mistake if you use it before touching any of the operation keys. This allows you to correct an entry error during a chain calculation without affecting previous results. Returns display to a single zero and decimal point (0.). (Striking the CE key after terminating a calculation will not affect the display.)

OPERATION KEYS

Instructs the calculator to multiply the displayed number by the next numeric entry. During chain calculations it will

simultaneously complete any previous calculation.

- Instructs the calculator to divide the displayed number by the next numeric entry.

 During chain calculations it will simultaneously complete any previous calculation.
- Instructs the calculator to add the displayed number to the next numeric entry. During chain calculation it will simultaneously complete any previous calculation.
- Use this key to instruct the calculator to subtract the next entry from the displayed number. During chain calculations it will simultaneously complete any previous calculation.
- Use this key to determine percentages or percentage rates as a whole number (rather than in terms of 1/100ths).
- Use this key to automatically obtain the square root of the displayed number. (During chain calculations, first complete the previous calculation with the key and then obtain the square root with the key.)
 - This key terminates calculations previously begun (division, multiplication, etc.). It is the operative key when calculating with constants. See pages 10-12 for examples of calculations.

NUMERIC AND SYMBOL DISPLAY

Your calculator displays up to 8 digits. The decimal point can be in any of 8 places. A ninth (leftmost) position is not a digit but is used to display a negative number or an OVERFLOW condition:

- This symbol indicates a negative number.
- E This symbol indicates an excessive number of digits has been entered. The numbers displayed will be the most significant digits entered. "Erase" the symbol and entry with the Clor CE key.
- This small box indicates a calculation has resulted in an "Overflow", that is, has exceeded the calculator's capabilities. NOTE: The displayed answer will be approximately correct but it will be necessary to mentally "move" the decimal point 8 places to the right. See examples on page 14.

FLOATING DECIMAL

Your calculation is equipped with full floating decimal capabilities and will carry results of calculations to the maximum number of places (decimal points) required by the answer, within the unit's 8-digit capacity. It does not round off fractions to the nearest number, but rather

truncates them. For example, 10 ÷ 6 would display 1.6666666 rather than 1.6666667.

CONSTANT FEATURE

An automatic built-in constant allows you to use a constant factor in addition, subtraction, multiplication, division, and percentage calculations. See examples on pages 10-12.

RECIPROCALS

Another feature of this calculator is its ability to obtain reciprocals $(1/\chi)$. Enter the number, depress the key, and depress the key twice. See example on page 8.

POWERS

Powers of whole numbers may be obtained by entering the number, depressing the Key, and then the key. The calculator will now display the square or second power of the number entered. Successive powers are obtained by continuing to depress the key. The exponent may be a positive or negative whole number. See example on Page 13.

SIMPLICITY OF ENTRY

Note that entering problems is very easy. You simply enter the problem in the same order as you would write it; for example, 4 = 2 = 2

SAMPLE CALCULATIONS

	ENTRY	DISPLAY	NOTES
73.50 + 5.14 =	C 73.5 + 5.14	0. 73.5 73.5 5.14 78.64	Not necessary to enter insignificant zeros
SUBTRACTION			
56.0 - 21.37 =	2012 ^c 56 2012 2 0erg	0. 56. 21.37	Illustrates full floating decimal capability
	amath Calcul		
MULTIPLICATION (1) 704.5 × 6.2 =	C 704.5 × 6.2 =	0. 704.5 704.5 6.2 4367.9	Insignificant zeros in result not displayed
(2) 5.5 × (-7.2) =	C 5.5 × 7.2	0. 5.5 5.5 5.5 7.2 -39.6	

	ENTRY	DISPLAY	NOTES
DIVISION			The state of the s
(1) 100 ÷ 6 =	C	0.	
	100	100.	
	-1-	100.	
	6	6.	
	=	16.666666	
(2) $100 \div (-6) =$	C	0.	
	100	100.	
		100.	
	Г	100.	
	6	6.	
0 004		-16,666666	
3) -100 ÷ 6 =	2 c oer	C VVOCI	lei
	-	0.	
	CHUCL	ulato <u>100.</u> /lu	
	6	-100.	
	=	-16.666666	
MIXED OR CHAIN CALCULATIONS		The second secon	
THE OH CHAIN CALCULATIONS	C 1.5	0.	
(1.5	1.5	
$\left\{ \frac{(1.5 \times 4) + 3}{6} \right\} -7.4 =$	× 4	1.5	bou has terminated the
6 5 -1.4 =	+	6	+ key has terminated the 1.5 × 4 calculation (=6)
	3	3	1.5 A 4 calculation (-0)
		1.5 1.5 4. 6. 3. 9.	key has terminated the previous
	6	6.	addition step (6 + 3)
	-	1.5	against steh (a .4. 2)
	7.4	7.4	
	=	-5.9	

	ENTRY	DISPLAY	NOTES
SQUARE ROOT			
√1.78 =	1.78	0. 1.78	Answer several to 7 decimal places
	$\sqrt{\chi}$	1.3341664	Answer correct to 7 decimal places
RECIPROCAL.			
(1) $1/5$ or $1 \div 5 =$	C	0.	
	2	0. 5. 5. 1.	
	C 5 ÷		Intermediate result
	=	0.2	
(2) $1/0.85$ or $1 \div 0.85 =$	2012 S eer		
	nath Calcu	0.95	
	=	1.1764705	
(3) 35 × 12	C	0.	
75 + 175	75 +	75. 75.	
	175	175.	
Problem may be stated:	÷	250.	
	=	1.	
$\frac{1}{75 + 175} \times \frac{35 \times 12}{1}$	=	0.004	
75 + 175 ^ 1	×	0.004	
	35 × 12	35. 0.14	
	12	12.	
	=	1.68	

	ENTRY	DISPLAY	NOTES
PERCENTAGE			
(1) Determine percentage 200.00 Base × 15% Percentage rate = Percentage	C 200 × 15 %	0. 200. 200. 15. 30.	% acts as equals key
(2) Discount: Determine net amount after discount 200.00 Base — 10% Discount — 0 2012	C 200 - 10 %	0. 200. 200. 10. 20. (180.)	Discount Total Cost
(3) Mark-up: Gross profit is a mark-up of base cost (Base + Percentage Rate) 200.00 Base + 15% Percentage rate Total amount	C 2000 U + 15 % =	0. 1200./U 200. 15. 30. 230.	Seum \$ Mark-up Total Cost
(4) On a base price of \$200.00, the gross profit desired is 10% of the selling price; therefore cost is equal to 90% of selling price. $200 = 90\% \ (\chi)$ then $\chi = 200$ 90% Where $\chi = \text{Selling Price}$	200	0. 200. 200. 90. 222.22222	(= \$222.22)

5) Finding percentage rate 40 is equal to what percent of 200?	С	-	
	U	0.	
	40	40.	
$40 = \chi\%$ (200)		40.	
	200	200.	
	%	20.	(20%)
5) Mixed percentage	C - 400	0.	
400 items at \$25.00 each less 20% dis	- 400	400.	
count (before duty) plus 15% import duty	y × 25	400.	
= total cost	25	25.	
	_	10000.	
	20	20.	* Di
	2 % erg	2000.	\$ Discount
			\$ Before Duty
	Cox Cul	atopoviu	\$ Duty
	=	9200.	Total Cost
CONSTANT			language (in the control of the cont
1) Addend 125 250 212	C 25 + 125	0.	
+25 +25 +25	25	25.	Enter constant number first
	+	25.	
		125.	
	=	150.	
	250	250.	
	=	275.	
	212	212. 237.	

				ENTRY	DISPLAY	NOTES
Minuend				С	0.	
(2) 100	100	100		100	100.	Enter constant number first
-25	-36	-80		_	100.	and the same of th
				25	25.	
				=	75.	
				36	75. 36.	
				=	64.	
				80	80.	
				=	20.	
ubtrahend				С	0.	
3) 125	250			-	0	Enter function first
-25	-25			25	25.	Enter constant number next
				2 125 125		
				125	125.	
				C= CL	g W-25. rn 125. ulato 100./lu	
				250	250.	
Multiplier			-		225.	
				C	0.	
4)				2.5	2.5	Enter constant number first
	< 2.5 =			X	2.5	
	< 2.5 =			100	100.	
(205)	< 2.5) >	(3=		-	250.	
				125	125.	
				=	312.5	
				205	205.	
				=	512.5	
				× 3	512.5	Illustrates constant factor is updated
					3.	to 512.5 when is keyed.
				200	1537.5	

			ENTRY	DISPLAY	NOTES
ivisor		16.0	C 6	0.	
5) 6 3	156	918	6	0. 6. 3. 2.	
3	3	3	3	6.	0-1-1-1-1-1-1-1-1
				3.	2nd entry in division is constant
			156	156.	
			156	52.	
			918	918.	
			=	306.	
ercenta	ge Rate		С	0.	100 - 300
20%			20	20.	Enter constant number first
20%	of 200		20 2 %oer	g \\\0.20 rr	
20%	of 300		×	0.20	
			150 CL	llato 30. VI	
			200	200.	
			===	40.	
			300	300.	
			=	60.	
rcenta	ge Base		C	0.	
10%	of 200 =		200	200.	Enter constant number first
15%	of 200 =		×	200.	
40%	of 200 =		10	10.	
			%	20.	
			× 10 % 15 % 40 %	15.	
			%	30.	
			40	40.	
			%	80.	

	ENTRY	DISPLAY	NOTES
POWERS			
(1) 16 ⁿ	C	0.	
	16	16.	
	C 16 ×	16.	1st power
	=	256.	2nd power
	==	4096.	3rd power
	=	65536.	4th power
		1048576.	5th power
	=	16777216.	6th power
	=	□ 2.6843545	Overflow. See Page 14
parting.	2012 coerg math Calcul		1st Power 2nd Power 3rd Power
CLEARING (Use of CE)			
1) 1.12		0	
+3.33	C 1.12	0. 1.12	
+4.13	1.12	1.12	
T4.10	+ 3.33	1.12 3.33	
		4.45	
	4.4	4.4	Freez in cotos
	CE	0.	Error in entry
	4.13	4.13	(Previous results still maintained)
	4.13	8.58	
		0.00	

	ENTRY	DISPLAY	NOTES
OVERFLOW Entry overflow 123456789	C 123456789	0. E12345678.	Last digit not displayed
Resultant overflow: 12345678 × 9 =	C 12345678 × 9 =	0. 12345678. 12345678. 9. □1.1111110	
Resultant Approximation with Overflow 98765432 × 9 =	0 98765432 XXXX	0. 98765432. \\\98765432.	
			Mentally "move" decimal point 8 points to right for approximate result of 888888880. (Correct result is actually 888888888.)
MISOPERATION 2 ÷ 0 =	C 2 ÷ 0	0. 2. 2. 0.	

MAINTAINING CALCULATOR

Cleaning

Case may be cleaned with alcohol. Display window may be cleaned with glass cleaner.

Storage

Unit should not be exposed for any prolonged period to temperatures below -40°F or above 150°F (these temperatures might be encountered in a closed automobile, for example).

TROUBLE SHOOTING

If a problem occurs, verify that the power switch is "ON" (slide switch pushed toward AC Adaptor - see Fig. 1).

Symptom	Power Source	Remedy Joe
No Display	Battery	Check or replace batteries; observe correct polarity
Weak Display	Battery	Check or replace batteries; observe correct polarity
No Display	AC	Check that AC/DC adaptor is plugged into a proper outlet
Display Lit But Result Incorrect	Either	Review operating instructions

If the remedies suggested do not cure the prob-

lem, refer to your service certificate for instructions.

NOTE: Batteries are not guaranteed by the calculator manufacturer. Also note that "AA" type batteries must not be returned if unit is returned for servicing.

POWER

An AC adaptor is supplied with 0311 models for your hand-held calculator from a standard 115 VAC wall outlet.

(AC adaptor is not included in 0310 models but

may be ordered separately.)

Batteries will have a longer life if you turn off calculator when not in use and if you will "clear" the calculator with the G after obtaining calculation results.

TO REPLACE BATTERIES (Models 0310 and 0311)

Your unit is shipped with four "AA" batteries. They are readily accessible by removing the battery cover on the bottom of the calculator case. Push the battery latch cover in the direction away from the label on the back of the case, and remove the cover. Remove old batteries and replace new ones according to the battery outline in the battery compartment. This will insure correct polarity of batteries. Failure to properly install the batteries will result in failure of the calculator to operate.

Batteries which may be used in your calculator 15 include but are not necessarily limited to the

following:

Company Eveready	Carbon Zinc 815, 915, 1015	Alkaline E-91	11.	Multiplication	Multiplicand (1st factor) Multiplier (2nd factor)	25 × 6 150
Mallory	M15R	MN-1500, SA15AA			Result (Product)	150
Panasonic	UM-3, UM-3D, UM-3N	AM-3	111.	Division	Dividend	150
	5AA. 7AA	815			Divisor	÷ 6
IF YOUR UN	IT IS EQUIPPE	D WITH			Result (Quotient)	25
NICKEL-CAD	MIUM BATTER	IES (MODEL 0312)	IV.	Addition	Augend	100
Owners of un	nits powered by	nickel-cadmium bat-			Addend	+25
		llowing precautions: than 12 hours with-			Result (Sum)	+25 125
out recha		operated for longer		cent: From La	COMMON TERMS tin "Per Centum." ("For	

periods, battery life may be reduced.)
(2) Recharge batteries for 12 hours, using

charger supplied with unit.

(a) Turn calculator to OFF position

(b) Plug charger cord into calculator and the

charger into any convenient AC outlet NOTE: The unit can be operated while the charger is "plugged in" to an AC outlet, but this will disconnect the charging circuit and charg-

The unit is protected against accidental overcharge of batteries.

(3) Nickel-Cadmium Battery Replacement Replacement should be performed only by an authorized service center. (See Service Certificate.)

ing will not occur during calculator operation.

GLOSSARY

16

ARITHMETIC TERMS

 I. Subtraction
 Minuend Subtrahend
 100 - 25

 Result (Difference)
 75

Percent: From Latin "Per Centum." ("For each hundred") Symbolized by "%". Thus 7% means 7 parts of 100 parts or 0.07 (7/100) of the whole.

The percent key % on your calculator computes percentages, percentage rates and percent bases automatically, including proper placement of the decimal point.

Constant: A quantity or factor in a calculation that remains the same in a series of similar

calculations.

Square and power: The square of a number is the result of that number multiplied by itself or the "second power", for example $12 \times 12 = (12^3) = 144$. Your calculator can automatically perform the squaring function or raise to higher powers, e.g. 3^3 or 3^5 (see page 12 for examples).

(C) 2012 Joerg Woerner Datamath Calculator Museum

Printed in U.S.A. P/N 02154-00